

**SPECIFICATION SHEET**

|                     |         |
|---------------------|---------|
| <b>Product Code</b> | VP*570# |
|---------------------|---------|

|                    |   |
|--------------------|---|
| <b>Description</b> | 13A 2 Gang 'Ingot' Switched Socket Outlet with Single USB Charging Outlet |
|--------------------|---|



| General Information    |   |
|------------------------|---|
| Dimensions             | 146mm x 88mm x 8mm (Excluding Gasket)   |
| Finishes Available     | Replace * with: AB (Antique Brass), BN (Black Nickel), BR (Polished Brass), CH (Polished Chrome), PN (Pearl Nickel), SB (Satin Brass), SC (Satin Chrome), and SS (Stainless Steel).   |
| Inserts Available      | Replace # with: WH (White) and BK (Black).<br>Black or White gasket supplied to match appropriate inserts.<br>(Antique Brass and Black Nickel are only available with back inserts).  |
| Material Composition   | Rear Housing: Nylon (PA66)<br>Front Plate: Stainless Steel<br>Terminals: Brass<br>Earth Strap: Mild Steel<br>Terminal Screws: Steel and Yellow Passivated<br>Internal Busbars: Formed Pressed Brass<br>PCB: Mixed Components<br>Silver "on-lay" copper/brass contacts |
| Back Box Depth         | 25mm – 47mm   |
| Cable Size             | L & N = Up to 3 x 2.5mm <sup>2</sup> solid or stranded, or up to 2 x 4mm <sup>2</sup> stranded conductors.<br>Earth = Up to 3 x 1.5mm <sup>2</sup> or 2.5mm <sup>2</sup> solid or stranded, or up to 2=2 x 4mm <sup>2</sup> stranded conductors                       |
| Terminal Size          | Live: 5mm<br>Neutral: 5mm<br>Earth: 5mm   |
| Switched               | Yes   |
| Double Pole            | No (Single Pole)  |
| Twin Earth             | Yes   |
| USB Charging Output    | 5V DC, 2.1A   |
| USB Output Connector   | USB Type "A"  |
| USB Standby Current    | 2mA   |
| Warranty               | 1 Year Domestic   |
| Standards              |   |
|                        | BS 5733 (BS 1363-2)<br>BS EN 60950-1 (USB Charger)<br>EN 61000-6-1/3, EN 61204-3 (EMC Directive)  |
| Additional Information |   |
|                        | Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram supplied with the relevant product.<br>Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.                   |