



## Packing

◆ Product Dimension	5000*10 mm
◆ Net Weight	300g

## Mechanical Specification

◆ Material	Silicon
◆ Ingress Protection(IP)	IP20

## Electrical Specification

◆ Power	12W
◆ Input Voltage	220-240V 50/60Hz
◆ Equiv Wattage	50W
◆ Standby Power	0.5W
◆ Protocol	WIFI+BLE
◆ Net Standard	2.4G WiFi IEEE 802.11 b/g/n
◆ Lifetime	25,000hrs
◆ Connection Range (open area)	30m(Within WIFI signal)
◆ Lumen	1200lm
◆ Colors	RGB+2700-6500K
◆ CRI	80
◆ Compatibility	Amazon Echo, Google Home

## Software Function

◆ CCT dimming	YES
◆ RGB dimming	YES
◆ Scenes	YES
◆ Music Sync	YES
◆ Plan	YES
◆ Schedule	YES

## Operation

1. Download Tuya Smart APP -You can search "Tuya Smart" in either APP Store or Google Play to install the APP.
2. Register a Tuya Smart account and sign in the app - You will be prompted to enter your mobile number or email address to register. The system automatically recognises your country / area. You can also select your country code.
3. When power on,the smart device will flash rapidly,then add relevant smart device to Tuya Smart App -Tap the icon+on the corner or"My device"page,choose your device type-Smart lighting, then follow the instructions in the App to connect the lamp.If not flashing rapidly,the smart device needs to be turned on/off/on/off/on/off/on, totally three times.
4. Enter Wi-Fi password, then connect. Make sure your router, mobile and lamp are as close as possible.
5. After connection, the lamp will appear in your list and you can control it from anywhere in the world.You can also rename the lamp and group more lamps.